



INSTALLATION & MAINTENANCE MANUAL

**NETRLxx**

## GENERAL INSTRUCTIONS

**These instructions should be read carefully and retained after installation by the end user for future reference and maintenance.**

**These instructions should be used to aid installation of the following product:  
NETRLxx**

## SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician
- Please isolate mains prior to installation or maintenance
- Check the total load on the circuit (including when this product is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker
- Please note the IP (Ingress Protection) rating of this product when deciding the location for installation
- This product is for indoor use only
- This product is Class II double insulated
- This product is IP20 rated
- This product is for indoor use only

## INSTALLATION

- Remove the front cover from the luminaire module by inserting a flat screwdriver into the four tabs on the side and levering off gently
- Clip the module into the faceplate (not included) from the rear, ensuring the correct orientation is observed. The four fixing tabs on the luminaire should pop out to secure the fitting
- Thread the module front cover over the head of the luminaire, align the tabs on the front cover with the tabs on the fitting, and press firmly into place
- Please note that the fitting is difficult to remove from the faceplate once installed. This is to prevent it from

falling out during use. It can be prised out from the rear of the faceplate using a flat screwdriver but this may cause deformation or damage

- Connect to the mains supply ensuring the correct polarity is observed:  
L – LIVE – Brown  
N – NEUTRAL – Blue
- Check all electrical connections are secure with all exposed copper within the terminal and no loose strands of cable
- Fit the unit into a suitable wall box taking care not to compress, damage or trap any cables. If using metal mounting boxes with four lugs, remove the top and bottom lugs or bend fully back
- Switch on and check for correct operation

## DIMMING PROCEDURE

The switch on this product is touch sensitive and requires only a light pressure.

To turn on / off	Short press
To dim up / down	Long press

The product has a memory function allowing the previously selected brightness level to be retained while switched off.

## WARNING

This product must be disconnected from the circuit if subjected to any high voltage or insulation resistance testing. Irreparable damage will occur if this instruction is not followed.

## GENERAL

This product contains a light source of energy efficiency class G to Regulation (EU) No. 2019/2015 and (UK) 2021 No. 1095.

This product contains a non-replaceable LED light source and a non-replaceable control gear.



Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the product.

This product is dimmable only using its own touch switch, it is not to be dimmed using a separate dimmer switch.

This product should be dismantled for disposal when it reaches the end of its life. Please see website for dismantling instructions.

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist.

## WARRANTY

This product has a warranty of 2 years from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

**SUPPLIED BY:**

**(UK) MANUFACTURER ML ACCESSORIES LTD,**  
UNIT E CHILTERN PARK,  
BOSCOMBE ROAD, DUNSTABLE LU5 4LT,  
WWW.MLACCESSORIES.CO.UK

**(EU) AUTHORISED REPRESENTATIVE**  
**SLV LIGHTING GROUP,**  
DAIMLERSTRASSE 21-23,  
52531 ÜBACH-PALENBERG, GERMANY  
**EMAIL: EPREL@GROUP.SLV.COM**

MADE IN CHINA

