



INSTALLATION & MAINTENANCE MANUAL

SA3040RWxx

GENERAL INSTRUCTIONS

These instructions should be read carefully and retained after installation by the end user for future reference and maintenance.

These instructions should be used to aid installation of the following product:

SA3040RWxx

SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician
- Please isolate mains prior to installation or maintenance
- Check the total load on the circuit (including when this luminaire is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker
- Please note the IP (Ingress Protection) rating of this product when deciding the location for installation
- Allow 50mm above and around the fitting for air dissipation (do not cover with insulation)
- This product is for indoor use only
- This product is Class II double insulated
- This product is IP20 rated

INSTALLATION

Note - If this luminaire is being used in conjunction with an external PIR or sensor, please confirm with the manufacturer of the sensors that they are compatible with LED luminaires.

- Provide power to the required point of installation
- Cut a suitable hole in the mounting surface as per the cut-out details (see Fig. 1) ensuring not to infringe with any joists, gas/water pipes or electrical cables




Fig. 1

- Remove the cover of the driver using a flat-head screwdriver
- Connect the driver to the mains supply ensuring the correct polarity is observed (see Fig. 2): L – Live (brown), N – Neutral (blue). The earth terminal is non-functional and only provided for convenience.




Fig. 2

- (0-10V dimmable driver SA3040RWAD only) Ensuring correct polarity is observed, carefully wire as shown in Fig. 3




Fig. 3

- Adjust the DIP switches on the driver to the required wattage (see Fig. 4)

DIP Switch	30W 750mA	35W 850mA	40W 950mA
1	OFF	ON	ON
2	OFF	OFF	ON

Fig. 4

- Refit the terminal cover on the driver
- Connect the fitting to the driver via the plug and socket
- Select the required colour temperature via the three-position switch on the luminaire flex
- Adjust the luminaire to the required angle of tilt – the tension can be adjusted by loosening or tightening the screws on the rear of the fitting
- Lift both spring clips on the sides of the fitting and push into the ceiling ensuring the driver is not resting against the luminaire
- Switch on and check for correct operation


WARNING

This product must be disconnected from the circuit if subjected to any high voltage or insulation resistance testing. Irreparable damage will occur if this instruction is not followed.

GENERAL

This product contains a light source of energy efficiency class A/B/C/D/E/F/G to Regulation (EU) No. 2019/2015 and (UK) 2021 No. 1095.

This product contains a non-replaceable LED light source and a control gear which can be replaced by a professional.



Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the product.

This product is non-dimmable (SA3040RW) / dimmable via a 1-10V dimmer (SA3040RWAD).

This product should be dismantled for disposal when it reaches the end of its life. Please see website for dismantling instructions.

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist.

WARRANTY

This product has a warranty of 5 years from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

SUPPLIED BY:
(UK) MANUFACTURER
ML ACCESSORIES LTD, UNIT E CHILTERN PARK,
BOSCOMBE ROAD, DUNSTABLE LU5 4LT,
WWW.MLACCESSORIES.CO.UK

(EU) AUTHORISED REPRESENTATIVE
SLV LIGHTING GROUP,
DAIMLERSTRASSE 21-23,
52531 ÜBACH-PALENBERG, GERMANY
EMAIL: EPREL@GROUP.SLV.COM
MADE IN CHINA

