

7		8		9	
		版本号		A / 0	
		首次制图日期		2024-1-25	
版本	日期	修正内容		修订者	
A / 0	2024-1-25	新图纸发行		刘培俊	

FRONT

80mm

Knightsbridge

These instructions should be read carefully and retained after installation by the end-user for future reference and maintenance.

These instructions should be used to aid the installation for the following products:
NETPIRxxx, NETPIRSxxx, NETTS1xx, NET2xxxx, NET12xxxx

SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician.
- Please isolate the mains prior to installation or maintenance.
- Check the total load on the circuit (including when this product is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker.

INSTALLATION

- Always ensure the wall surface is flat and smooth.
- When using Class I accessories, all earth connections must be made and maintained. Use green/yellow sleeving on earth conductors that are not insulated.
- Check all electrical connections are secure with all exposed copper within the terminal and no loose strands of cable.
- Fit the unit into a suitable modular frame and wall box taking care not to compress, damage or trap any cables. If using metal mounting boxes with four lugs, remove or bend fully back the unnecessary ones.
- Connect to the mains supply ensuring the correct polarity is observed by following the relevant wiring diagram

1.

WARNING

Products with USB and LED or Neon indicators must be disconnected from the circuit if subjected to any high voltage or insulation resistance testing. Irreparable damage will occur if this instruction is not followed. Please note this kind of damage will void the warranty.

WARRANTY

This product has a warranty of 25 years (2 years on electronic products) from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

4.

NETPIRxxx or NETPIRSxxx NETTS1xx

PIR Switch Module
L (LIVE) = red or brown
N (NEUTRAL) = black or blue

Touchless Switch Module
L (LIVE) = red or brown
N (NEUTRAL) = black or blue

2.

NET2xxx or NET12xxx

1G 2-way modular 1G intermediate modular

L IN L IN-1 L IN-2

COM TOP TOP

L1 L1 L1

L2 L2 L2

L OUT-1 L OUT-2 L OUT-1 L OUT-2

3.

- Switch on and check for correct operation.

160mm

BACK

Manufacturers Declaration of Conformity
For ML Accessories (Knightsbridge)
Electrical products in accordance with CE marking
ML Accessories Ltd. declare that all products have been designed, manufactured, and tested in accordance with the requirements of the relevant legislation

UKCA marking legislation
UK SI 2016 No. 1091 Electro Magnetic Compatibility Regulations 2016
UK SI 2016 No. 1101 The Electrical Equipment (Safety) Regulations 2016
UK SI 2012 No. 3032 Restriction of the use of Certain Hazardous Substances in Electrical and Electronic Equipment Regulations 2012

UK SI 2017 No. 1206 Radio Equipment Regulations 2017
UK SI 2021 No. 1095 The Ecodesign for Energy-Related Products and Energy Information (Lighting Products) Regulations 2021

Included Legislation
UK SI 2008 No. 2852 UK REACH
UK SI 2013 No. 3113 WEEE

Safety Standards
Full individual declarations and specific safety standards applicable to relevant product series can be found on our website www.mlaccessories.co.uk
We hereby declare that the equipment named above has been designed to comply with the relevant sections of the above referenced specifications. The products comply with all essential requirements of the directives.

Catherine Connolly Lee Saunders
CEO Technical Assessment & Compliance Manager

5.

Knightsbridge

230V
50Hz

IP20

ML ACCESSORIES LTD

UKCA **CE** **UKCA** **CE** **UKCA** **CE**

7.

Manufacturers Declaration of Conformity
For ML Accessories (Knightsbridge)
Electrical products in accordance with CE marking
ML Accessories Ltd. declare that all products have been designed, manufactured, and tested in accordance with the requirements of the relevant legislation

CE marking legislation
In accordance with the following Directives:
2014/35/EU Low Voltage Directive
2014/30/EU EMC Directive
2014/53/EU Radio Equipment Directive

Including Legislation
1907/2006 REACH
2015/863 RoHS
2011/65/EU ERP

Safety Standards
Full individual declarations and specific safety standards applicable to relevant product series can be found on our website www.mlaccessories.co.uk
We hereby declare that the equipment named above has been designed to comply with the relevant sections of the above referenced specifications. The product complies with all essential requirements of the directives.

Catherine Connolly Lee Saunders
CEO Technical Assessment & Compliance Manager

6.

Manufacturers Declaration of Conformity
For ML Accessories (Knightsbridge)
Electrical products in accordance with UKCA marking
ML Accessories Ltd. declare that all products have been designed, manufactured, and tested in accordance with the requirements of the relevant legislation

UKCA marking legislation
UK SI 2016 No. 1091 Electro Magnetic Compatibility Regulations 2016
UK SI 2016 No. 1101 The Electrical Equipment (Safety) Regulations 2016
UK SI 2012 No. 3032 Restriction of the use of Certain Hazardous Substances in Electrical and Electronic Equipment Regulations 2012

UK SI 2017 No. 1206 Radio Equipment Regulations 2017
UK SI 2021 No. 1095 The Ecodesign for Energy-Related Products and Energy Information (Lighting Products) Regulations 2021

Included Legislation
UK SI 2008 No. 2852 UK REACH
UK SI 2013 No. 3113 WEEE

Safety Standards
Full individual declarations and specific safety standards applicable to relevant product series can be found on our website www.mlaccessories.co.uk
We hereby declare that the equipment named above has been designed to comply with the relevant sections of the above referenced specifications. The products comply with all essential requirements of the directives.

Catherine Connolly Lee Saunders
CEO Technical Assessment & Compliance Manager

5.

140mm

注印刷要求:
1. 双面黑色印刷, 前四格+后四格
2. 印刷展开尺寸: 160X140mm
3. 折成型后尺寸: 80X70mm

博罗联益照明电器制品有限公司 Luen Yick (Boluo) Lighting & Electrical Mfg. Co., Ltd.						
材 料	80G双胶纸		名 称	MLA品牌NETxxx说明书		
硬 度	净重	g	图 号	绘图	审核	
表面处理	颜色	白底黑字	IL1696A			
未注尺寸公差	0 ± 0.5	比例	1: 1			零件号
未标公差角度	0.0 ± 0.2 0.00 ± 0.1 ± 1°	单位	mm			ILO1696NLA

A 图纸尺寸与图形不成比例
B 图中带"*"号的尺寸为重点尺寸