

Product Code

F07733

2W CORAKIT DUOX PLUS PANEL



Reference

7733

EAN

8424299077338

Description.

Description

The CoraKit panel follows the design of its predecessor, the Cora panel, combining elegance and simplicity. It also includes visual and audible signals that enhance the user experience. Surface mounting is very easy.

Configuration and management are very simple and can be done entirely from a mobile phone, tablet, or PC via a web server, without needing to open the panel. The installer simply stands in front of the panel and connects to its Wi-Fi access point. This allows them to manage audio volume, voice prompts for door opening, and other parameters.

Technical Details

System

- Technology: DuoxPlus (digital audio/video over 2 non-polarized wires)

- Time to respond or open after the call(s) are made: 30
- Talk time (s): 90
- Conversation privacy: Yes

Facility

- Wiring: 2 non-polarized wires
- Mounting: Surface

Environmental

- Operating temperature: [-25, +55]
- Environmental Protection Rating (IP): 54
- Relative humidity (non-condensing): [5%, 95%]

Mechanics

- Dimensions (height x width x depth) mm: 166 x 89 x 27.5
- Impact resistance rating (IK): 07

Electrical

- Removable connection strips.
- Connection terminals:
 - B,B Bus DUOX: power, data, audio and video
 - C, NO, NC Relay. Dry relay contact
 - +12 **Door opener** . 12Vdc output (12V is only available upon activation).
 - BS - **Exit Button** . Hallway push button for door opening

Start	Rest with WIFI	Standby mode without Wi-Fi	Call	Active Video	Active Audio and Video
125 mA	115 mA	92 mA	233 mA	150 mA	270 mA

Video

- Angle (H x V): 118° x 70°
- Zoom to view an area of the image (up to 10 selectable areas).
- Scene lighting using LEDs (can be deactivated):
 - Color night vision (if LEDs are activated).

Pushbuttons and cardholders

- Home call buttons: 2.
- Front removal of the card holder to facilitate changing the name card.
- Backlit card holder.
- It is possible to assign any DUOX (000001-999999) call address to the pushbuttons.
- It is possible to configure the push buttons to call a predefined concierge.

Functional

- Call to apartment
- Call to concierge
- Access to the web server for configuration
- Accessibility icons that report the communication status (calling, Conversation, Busy channel, Open door).
- Call confirmation sound (tell) (can be disabled).
- Voice message "Open Door" in 32 languages (can be deactivated). Two languages can be selected for the message to be played in both.
- Customizable "Open Door" voice message (a custom audio file can be uploaded).
- +12V output (for low-power DC door openers)

Details.

Weight (kg)

0.6

Packaging measurements

(height x width x depth) cm

17,2x4,3x11

Video Door Entry system

Technologie

DUOX

Manuals

- 970357 Guia Rapida Cora
KIT V05_26.pdf

Training video

- <https://youtube.com/playlist?list=PLf1YNFmssC34GXEkdseiJF1fh8c1QX8gQ&si=hMmBEbipAI8gKG-Z>