



8451V

QUADRA KIT AND WIFI MINI HF, S2



The kit consists of no. 1 external unit Quadra art. 4893M, no. 1 power supply art. 1209, no. 1 monitor Mini hands-free Wi-Fi art. 6741W and no. 1 line termination terminal art. 1216. The kit is pre-programmed and ready to use.

AWARDS

DESIGN
MILANO



DESIGN **PLUS**
awarded by **Light Building**



8451V

QUADRA KIT AND WIFI MINI HF, S2

KIT PRODUCT



4893M

QUADRA ENTRANCE PANEL W/ BUTTONS. 2 WIRES

Quadra series wall-mounted external video entry unit with mechanical buttons. Die-cast aluminium faceplate, wide-angle colour camera and a single LED for nighttime lighting. Indicator LED for call sent, lock-release activated, audio activated and system busy. Adjustment of speaker volume and audio balance. Power supply from bus line. External unit dimensions: 95x195x28 mm.

MAIN FEATURES - 4893M

Type:	Monoblock
Type of finish:	Die-cast aluminum
Audio/video system:	Yes
Wall-mounted:	Yes
Type of sensor:	1/4" CMOS
Lens size (mm):	2.1
Diagonal viewing angle (°):	100
Minimum colour lighting (lux):	0.1
Horizontal resolution (TVL):	550
Signal/noise ratio (dB):	48
Maximum current absorption (mA):	250
Clamps:	LL RTE COM DO SE- SE+C NC NO
Buttons to call:	Yes
Total buttons:	4
Microphone volume control:	Yes
Loudspeaker volume control:	Yes
Operating temperature (°C):	-25 ÷ 55
RH operating humidity (%):	25 ÷ 75
IP protection rating (IP code):	IP54
Vandal Resistant rating (IK code):	IK08
Backlighting colour:	White



6741W

MINI HANDSFREE WIFI MONITOR, S2

Wall-mounted hands-free monitor with full-duplex audio and 4.3" / 16:9 colour screen. It is equipped with a Wi-Fi port to allows calls forwarding to mobile devices. Allows brightness control, plus adjustment of the ringtone volume, which can be customised by choosing one of several different melodies.

Equipped as standard with 8 sensitive touch back-lit controls for audio activation, door-opening, self-ignition, switchboard call, privacy service and LED signalling for the door status. Manages floor door calls as standard.

Complete with 2 x 8-position dip-switch for user code programming and button programming. The wall-mounting backplate and riser distribution terminal art. 1214/2C are included. The monitor can only be used in 2-wire system Simplebus 2. Dimensions: 115x160x22mm.



8451V

QUADRA KIT AND WIFI MINI HF, S2

GENERAL DATA - 6741W

Product height (mm):	160
Product width (mm):	115
Product depth (mm):	22
Product weight (g):	400
Product color:	White RAL9003
Material:	ABS
Desk base-mounted:	Yes, with a dedicated accessory



1209

2-WIRE VIDEO KIT POWER SUPPLY UNIT

33 VDC power supply unit with overload and short circuit protection devices. It has two separate continuous outputs: one for external unit and one for the monitor power supply. Input voltage 110-240 VAC. Dimensions: 106 x 62 x 89 mm (6 DIN modules).

MAIN FEATURES - 1209

Supply voltage (VAC):	110÷240
Input connector:	Terminal block
Applicable to DIN rail:	Yes
Number of DIN modules:	6
Max. current delivered (A):	1.2



1216

VIDEO RISER TERMINATION FOR SIMPLEBUS


Line termination terminal. To be mounted at the end of the riser, according to the indications given in the technical documentation, to optimise distribution of the signals.



8451V

QUADRA KIT AND WIFI MINI HF, S2

ACCESSORIES



4791

Adapter plate for Quadra

Plate allowing installation of the Quadra external unit in 1- and 2-module flush-mounted boxes by Comelit, Bticino and Urmet. Dimensions 137x236 mm



4792

RAIN SHIELD FOR QUADRA ENTRANCE PANEL

Rain shield in painted aluminum for Quadra entrance panel, grey colour. Dimensions (W x H x D): 99 x 210 x 41 mm.



4793MB

BLACK FACEPLATE FOR QUADRA W/BUTTONS

Black faceplate for Quadra entrance panel with mechanical buttons.



4793MC

CORTEN FACEPLATE FOR QUADRA W/BUTTONS

Corten color faceplate for Quadra entrance panel with mechanical buttons.



4793MA

ALUMINIUM FACEPLATE FOR QUADRA W/BUTTONS

Aluminium colour faceplate for Quadra entrance panel with mechanical buttons



1217

NAME TAG SHEETS FOR QUADRA ENTRANCE PANEL

The kit contains 10 sheets of adhesive labels for nameplates



8451V

QUADRA KIT AND WIFI MINI HF, S2

ACCESSORIES



1235A

NAMEPLATE LABEL PRINTING SOFTWARE

Dedicated software for the creation and printing of nameplate and information labels for Ikall, Vandalcom, Quadra and 316 Analog entrance panels. Requires use of adhesive labels art.1217, 1218, 1219 or art.1220. This software is available to download free of charge from the Comelit website



6710

BACKPLATE AND DISTRIBUTION TERMINAL FOR MINI MONITOR

Wall-mounting or residential series box backplate for MINI monitor, /BM versions with handset featuring magnetic induction for hearing aid wearers. Also includes riser distribution terminal Art. 1214/2C. Dimensions 145x100x4 mm.



6720

Access. cables external passage for MINI HF. S2

Wall support bracket for handsfree Mini monitor allowing thru-routing of external cables.



6732

DESK BASE FOR HANDSFREE MINI MONITOR


Desk base for desktop conversion of Handsfree Mini monitor. Complete with 1x 2 metre cable with RJ45 connector to connect monitor terminals to the coupler or domestic series socket. Dimensions: 140x190x140mm.



1209

2-WIRE VIDEO KIT POWER SUPPLY UNIT

33 VDC power supply unit with overload and short circuit protection devices. It has two separate continuous outputs: one for external unit and one for the monitor power supply. Input voltage 110-240 VAC. Dimensions: 106 x 62 x 89 mm (6 DIN modules).



1229A

ADDITIONAL RINGTONE ACCESSORY. S2

Wall-mounted accessory for additional ringtone for direct connection to 2-wire bus. Allows ringtone selection and adjustment of ringtone volume with privacy function, equipped with dip switches for user code programming, floor door call input terminals and call repeat. Fitted with distribution terminal art. 1214/2C. Dimensions: 125x95x24 mm.



8451V

QUADRA KIT AND WIFI MINI HF, S2

ACCESSORIES



1256

ACTUATOR RELAY

Intelligent Simplebus device for controlling a 12-24 V relay contact. If used in mixed audio/video systems, the actuator relay needs a video filter to be purchased separately. Power supply: 12V AC or 20V DC. Dimensions: 66x85x35 mm (4 DIN modules).



1404

DIGITAL SWITCHING DEVICE. 2-WIRE SYSTEM

Audio/video switching module for Simplebus 2 2-wire digital systems. To be used in systems with more than one entrance. Power supply from bus line. Dimensions: 60x85x35 mm (4 DIN modules).



1405

DIGITAL EXCHANGE 2 QUADRA INPUTS. S2

Audio/video switching module for audio/video kit systems. For use in systems with a maximum of 2 entrances with Quadra series external unit. Power supply from bus line. Dimensions: 35x90x58mm (2 DIN modules).



1409

ACCESSORY FOR REMOTE COLOUR CAMERAS, 2-WIRE SYSTEM

Remote camera module for Simplebus 2 2-wire digital systems. Allows management of up to 3 colour cameras in cyclical sequence from door entry monitors using a dedicated button. 12 Vac or 20 Vdc power supply. Dimensions: 60x85x35 mm (4 DIN modules).