



| General Information        |               |
|----------------------------|---------------|
| Dimensions (mm)            | 129 x 73 x 50 |
| Materials                  | ABS           |
| Mounting                   | Surface       |
| Warranty (Years)           | 2             |
| Environment                |               |
| Ingress Protection         | IP20          |
| Operating Temperature (°C) | 0 to +50      |

| Supply & Power        |                                             |
|-----------------------|---------------------------------------------|
| Supply Voltage (V AC) | 100 - 230                                   |
| Input Type            | Coil (to activate lock output switch over)  |
| Activation Type       | Energise with a Normally Open Clean contact |
| Output Type           | Normally Open or Normally Closed            |
| Number of Outputs     | 2                                           |
| Constant Output       | 12V @ 1A                                    |
| Lock output           | 12V DC @ 1.5A                               |

**Supplied** Fixing Screws, and Wall Plugs, User Manual, Battery Cables

| Features                                                                                                                                                      | Accessories                                                                                                                                                                                                                                                                                                                      |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Optional Battery Backup<br>Suitable for both Fail-Safe & Fail-Secure locks<br>Can be powered from a battery upon mains failure, and charge SLA 12V Batteries. | BAT32: 12V 3.2Ah SLA Battery<br>BAT7: 12V 7Ah SLA Battery<br>BAT18: 12V 17Ah SLA Battery<br>EV-EXIT: Push to Exit Release Button<br>EV-EBG: Green Emergency Break Glass<br>ENTERD: Flush Electronic Lock<br>ENTERD-YLR: Surface Electronic Lock<br>EV-ML-250: Electromagnetic Lock<br>EV-ML-500XT: External Electromagnetic Lock |

|                               |                                                                       |
|-------------------------------|-----------------------------------------------------------------------|
| <b>Additional Information</b> | Upon Power Failure, if a battery is connected it will power the unit. |
|-------------------------------|-----------------------------------------------------------------------|

