

Keyswitch Reset Point

Part No. **NC8991RR**



Overview

- A secure keyswitch-operated reset point specifically designed to cancel Emergency calls generated by an NC302RXC master infrared ceiling receiver.
- To operate, momentarily turn the keyswitch to the ISOLATE position to reset a call.
- Always return the keyswitch to the ON position after reset (leaving it in the ISOLATE position will disable the NC302RXC receiver's emergency call facility).
- Mounts on a standard UK 25mm single gang flush or surface back box.



Technical Specifications

Quiescent current	0mA (none).
Alarm current	Determined by the type of control equipment and number / type of field devices connected to the system.
Controls	Reset keyswitch (cancels Emergency calls generated by an NC302RXC infrared ceiling receiver). Momentarily turn the keyswitch to the ISOLATE position to reset a call.
Connections	-Ve (Negative); +Ve (Positive); SW (Switched Output).
Product dimensions (mm)	87 W x 87 H x 34 D mm. Mounts on a UK 25mm single gang back box.
Construction & finish	Plastic.
IP Rating	IP41.
Weight	80g
Operating conditions/temperature	-5°C to +40°C. Max. relative humidity 95% non-condensing.
Notes	Always return the keyswitch to the ON position after reset (leaving it in the ISOLATE position will disable the NC302RXC receiver's emergency call facility).