

Quantec Addressable Call Point, Button Reset c/w Iconised Label & Remote Socket

Part No. **QT602E**



Overview

- A programmable addressable call point c/w iconised label and remote jack socket for use with C-TEC's Quantec Addressable Call System.
- Includes a Call button, Reset button and red/green confidence light.
- Can make up to 5 levels of call - Standard, Ensuite, Help Required, Emergency, Presence & Attendance (dependent on configuration and ancillary devices used). Attack and Attendance calls can also be made if connected to compatible infrared receiver.
- Remote socket allows the connection of optional tail call leads, pressure mats, etc.
- Can be programmed to operate in a multitude of ways using a QT423 configurator.
- Connections provided for ancillary devices such as ceiling pulls, overdoor lights, infrared receivers and more.

Technical Specifications

Power requirements	Nominal 24V DC (from Quantec Controller/Network)
Quiescent current	Less than 3mA.
Alarm current	14mA.
Indicators	Red/green confidence LED.
Controls	Iconised Call button; Iconised Reset button.
Connections	Net +; Net -; R; G; L+; SW; IR; SLV.
Expansion connections	R; G; L+; SW; IR & SLV terminals allow the connection of optional dummy/extender overdoor lights, dummy/extender call points, dummy/extender ceiling pulls and dummy/extender infrared receivers.
Onboard 6.35mm Remote Jack Socket	Yes - for the optional connection of tail call leads/pear pushes, pressure mats and movement detectors.
Onboard Sounder	No



Onboard Infrared Receiver	No.
Product dimensions (mm)	86 W x 86 H x 30 D mm. Can be mounted on a standard UK 25mm single gang flush or surface back box.
Construction & finish	Plastic.
IP Rating	IP20.
Weight	72g.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.

