

# AJAX

## FIREPROTECT PLUS



Wireless fire detector with temperature and carbon oxide sensors that monitors security in the room twenty four hours a day and immediately notifies of dangerous CO levels, smoke and sharp jumps in temperature.



Ready to operate straight out the box: the battery is already installed, therefore there is no need to disassemble the detector. With one click, it can be connected to the hub in the mobile application. It can be mounted on the SmartBracket in just a few minutes.

## Specification

<b>Classification</b>	Radio channel smoke detector with temperature sensor and built-in siren
<b>Type of detector</b>	Wireless
<b>Installation method</b>	Indoors
<b>Compatibility</b>	Operates with Hub, Hub Plus, ReX, ocBridge Plus, uartBridge
<b>Sensing element</b>	Photoelectric, CO and temperature sensors
<b>Activation threshold</b>	+54°C to +65°C
<b>Type of notification</b>	Sound/light
<b>Volume of built-in siren</b>	85 dB
<b>Alarm signal delivery time</b>	0.15 s
<b>False alarm filter</b>	+
<b>Interconnected alarms</b>	+
<b>Power supply</b>	Battery: Two CR2 batteries Power supply voltage: 3 V Battery life — up to 4 years Backup power supply: battery Cr2032
<b>Additional temp sensor</b>	Available
<b>Permissible humidity</b>	Up to 80%
<b>Anti-sabotage</b>	Protection against fraud Jamming detection Tamper-resistant
<b>Remote setting and testing</b>	+
<b>Dimensions</b>	132x132x31 mm
<b>Weight</b>	220 g
<b>Certification</b>	CE 1922
<b>Complete set</b>	FireProtect detector SmartBracket mounting panel 2 x CR2 batteries (pre-installed) 1 x CR2032 backup battery (pre-installed) Installation set User's guide