

Wireless Floodlight Camera

 **IP65**

NO WIRING

EASY INSTALLATION

NO MONTHLY FEES

SKU Code: SHA5344, SHA5345



1080P



PIR



Viewing Angle



2-way audio



Control light
switch



Local storage



IP65



10400 mAh
Rechargeable Battery

Features:

- ▶ 1080P Full HD video quality
- ▶ 120° Wide viewing angle
- ▶ Built in 2.4G WiFi antenna
- ▶ Two-way audio
- ▶ 6pcs 850nm LED IR distance up to 8m
- ▶ PIR motion detecting distance up to 8m
- ▶ Low power, remote wake up by PIR detection or app manually
- ▶ Includes 4 pcs 18650 battery 10400mAh

- ▶ 2pcs spotlight combination up to 400LM
- ▶ Support smart human filter and motion zone settings
- ▶ Support Smart siren
- ▶ Support B/W & full color night vision
- ▶ Local storage MicroSD card up to 128G (not included)
- ▶ IP65-Certified weatherproof
- ▶ Flexible installation without wiring


Technical Specifications:

| | |
|----------------------------|-------------------------------------|
| SKU | SHA5344 |
| Image Sensor | 1/3" Color CMOS |
| Display Resolution | 1080P@15fps(1920*1080) |
| Mini. Illumination | 0 Lux (with infrared led on) |
| Focal Length | 2.8mm |
| Viewing Angle | 120° |
| LED | 6pcs 850nm LED IR distance up to 8m |
| Spotlight | 400LM |
| Day night mode | Auto change with IR-CUT removable |
| Image Compression | H.264 |
| DNR | 3D Digital noise reduction |
| WDR | Digital wide dynamic range |
| Audio | Built-in Mic & Speaker |
| LED indicator Light | Blue, Red |
| Motion Detection | PIR human motion detection 8m |
| Working Temperature | -20°C ~ 60°C |





Solar Silicon Crystal Panel



 **5**
Watts

 **IP65**
Weatherproof

Technical Specifications:

| | |
|---|---|
| SKU | SHA5345 |
| Solar Silicon | Single Crystal Cell |
| Power | 5W ±5% |
| Working Voltage | 6V ±5% |
| Working Current | 830mA ±5% |
| Efficiency | ≥20% |
| Working Temperature | -20°C ~ 60°C |
| Working Humidity | 20% ~ 95% non-condensing |
| Size | 169*159*2.8mm |
| Texture of material | Plastic shell |
| Backplane color | white |
| waterproof | IP65-Certified |
| Cable Length | 2.9m with Micro USB interface |
| Silica gel plug | Match for E93C or E938 |
| Wall mount Bracket | Support |
| Charging (For Li-battery camera) | |
| 2pcs 18650 battery 5200mAh | About 8 hours full of sufficient sunlight |



Note:

- ▶ The performance parameters of the solar cell output nonlinear change deviates from the standard conditions
- ▶ Because of crystalline silicon properties parameter discreteness obviously, the weak light electrical have differences
- ▶ The solar cell output voltage depends on the load voltage and watt level or nominal voltage of the battery
- ▶ This product can't contact with strong corrosive objects,
- ▶ To prevent the hard objects from scratching the surface during operation



Warning

- This product should be installed or maintained by trained electricians.
- Check integrity of the products when unpack the package and make sure there are no any damages, otherwise please call distributors for replacement.
- The distance between the light fixture and any flammable materials must be more than 20cm. The distance between the upper part of the installed light fixture and the ceiling must not be less than 2cm. The light fixture must not be installed into ceilings or walls that contain heat-insulating material.
- Please make sure to cut off power supply before installation, replacement or removal.
- Please read manual carefully and wire correctly.
- Do not remove the stickers on drivers or light fixtures
- Never leave children unattended in the vicinity of the light fixtures and do not allow them to play with electrical devices
- Never allow the fixture to come into contact with open flames or external heat sources, or UV rays.
- The products need special treatment of recycling after service time.

Thank you for choosing ENER-J!

Customer satisfaction is our TOP priority, please let us know how you felt about your experience. Happy? We are so happy that you are pleased with our product. Feel free to express your newfound joy! Share your experience by writing a review.

Not Happy? If you are not fully satisfied with the item you received, have any problems like damages, or questions, please contact us. We typically respond within 24-48 hours.

Stuck? Confused?

Contact our Technical Support team on:

T: +44 (0)1291 446 105 E: support@ener-j.co.uk

Lines are open Mon - Fri (8am to 4pm)