

ESP Device Address Programmer

TCH-B200



(shown with sensor fitted – not supplied)

Features

- ▶ Lightweight design
- ▶ Quick and reliable addressing
- ▶ Over 8000 address settings from one battery
- ▶ Displays sensor analogue value

Description

Model TCH-B200 is a hand held address programmer designed to address the ESP range of Sensors and all other addressable devices such as wall sounders, mini-modules and manual call points (with the use of a programming lead – sold separately).

The unit is designed to be light, robust and easy to use and operates from a single PP3 size battery, which gives the capacity for up to 8000 operations. The programmer is also capable of displaying the sensor analogue values.

Specification	
Ordering Codes	TCH-B200
	PL-3 (programming lead)
Battery Type	9 V dc
Operating Temperature Range	-10 °C to +50 °C
Colour / Case Material	White / ABS
Weight (g) / Dimensions (mm)	140 (Including Battery) / L160 x D30 x W99.5