

Product Code: Q551.13.13

Luckinslive 398794332

Description: Astro Zone 3, 3 Pin and Battery Back Up, 1 On/Off and Optional Early Off



General Information

Dimensions (mm)	146.5 x 105.7 x 82
Display	24 Hour Dial
Timing Accuracy	5 Minutes / Year
Time Base	Quartz Crystal
Mounting	Surface Mounting
Base Type	3 Pin
Warranty (Years)	5

Programming

Programming Schedule	24 Hour Program
Available Operations	1 ON/OFF Period
Dial Calibration	Zone 3
Setting Accuracy	+/- 3 Minutes
Sunrise/Sunset Time Offset (Mins)	(+/-) 45
Day Omission	No
Temporary Override Facility (Manual Button)	Advance to "OFF", When Program "ON" and will Remain "OFF" Unit Next "ON" Operation and Vice Versa

Supply & Power

Supply Voltage (V AC)	230
Power Consumption (W)	0.6
Power Consumption (mA)	0.6W @ 230V
Cable Size (mm²)	0.5 - 4
Power Reserve	20 Days
IEC Protection Class	Class I (Must be Earthed)

Environment

Ingress Protection	IP20
Operating Temperature (°C)	0 to +50

Features

Optional Early Off

Outputs

Number of Outputs	1
Relay/Contact Type	SPST
Relay Voltage - Maximum (AC)	230
Output Relay Resistive Load Rating (A)	20
Maximum LED Lamp Load Rating (W)	3600 @ 230V
Maximum Inductive Current Rating (A) (0.6pf)	5
Maximum Inductive Current Rating (A) (0.8pf)	12
Maximum Incandescent, Halogen Lamp Load Rating (W)	3600
Maximum Fluorescent Lamp Load Rating (W)	1980
Maximum Discharge (Sodium, Mercury, Metal Halide) Lamp Load Rating (W)	3600
Maximum Fluorescent Lamp Load Rating (W)	1980

Accessories

110469: FD930 Conduit Box Time Switch

