>Knightsbridge

DATASHEET



BPLEDS

14W LED Gear Tray with Microwave Sensor

www.mlaccessories.co.uk

| MLA PART CODE | BPLEDS |
|-----------------------|-----------------------------------------|
| DESCRIPTION | 14W LED Gear Tray with Microwave Sensor |
| NET WEIGHT (KG) | 0.64 |
| FINISH | White |
| DIMENSIONS (MM) | Diameter - 246 Projection - 38 |
| CONSTRUCTION | Construction - CEM-1 |
| CLASS | II |
| WATTAGE (W) | 14 |
| LAMP TECHNOLOGY | SMD LED |
| LUMENS (LM) | 1400 |
| LUMEN TOLERANCE | 5% |
| EFFICACY (LM/W) | 100.8 |
| CIRCUIT WATTAGE (W) | 14.2 |
| ССТ | 4000K |
| LIGHT COLOUR | Cool White |
| CRI | >80 |
| SDCM | <6 |
| RUNNING CURRENT (A) | 0.064 |
| DISPLACEMENT FACTOR | >0.9 |
| LIFE SPAN (HRS) | 25,000 |
| DIMMABLE | No |
| OPERATING TEMPERATURE | -5~50°C |
| INPUT VOLTAGE | 230V 50Hz |







Xnightsbridge

| DRIVER | DRIVER TYPE - Constant Current MAX. OUTPUT - 12W OUTPUT VOLTAGE - 0-26V OUTPUT CURRENT - 470mA POWER FACTOR - >0.9 EFFICIENCY FULL LOAD - 84.6 ISOLATION - SELV AMBIENT TEMPERATURE (Ta)5~50°C CASE TEMPERATURE (Tc) - 75°C |
|------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| SENSOR TYPE | Microwave |
| OPTIMUM DETECTION RANGE (M) | 1-8 |
| SENSOR DURATION | 10sec - 30min |
| SENSOR LUX SETTINGS | 10 - 2000 |
| WARRANTY | 3year(s) |
| MANUFACTURED IN ACCORDANCE WITH | BS EN 60598 |
| ORIGIN OF MANUFACTURE | China |
| DECLARATION OF CONFORMITY (HELD ON FILE) | Yes |
| EAN | 5055832970002 |

Date Created: 03/04/2023 13:06





